

H Series HA-3010

10 Band Handheld 3G、4G with Wi-Fi、5G、Remote、GPS Jammer

NEW Next Generation digital cell phone jammer top of the range; a mobile device to help circumvent disturbances or noise from cellular phone calls - the latest high-power hand-held cell phone and Wi-Fi jammer with an internal, high-capacity battery, universally compatible with new (LTE, Wi-Max) 4G / 3G / 2G / Wi-Fi / 5G/GPS networks. Selectable dip switches on the side for choice of jamming bands or save battery power.



Specifications

Frequency band with output power:

- RF 750 ~ 810 MHz: maximum output power of **1** watt. (4G LTE)
 - RF 870 ~ 965MHz: maximum output power of **1** watt. (GSM)
 - RF 1800 ~ 1920MHz: maximum output power of **1** watts. (GSM.CDMA)
 - RF 2110 ~ 2170MHz: maximum output power of **1** watt. (3G)
 - RF 2400 ~ 2500MHz: maximum output power of **1** watt. (WIFI)
 - RF 2620 ~ 2690MHz: maximum output power of **1** watt. (4G LTE)
 - RF 1560 ~ 1620MHz: maximum output power of **1** watt. (GPS L1)
 - RF 1200 ~ 1280MHz: maximum output power of **1** watt. (GPS L2)
 - RF 5300 ~ 5900MHz: maximum output power of **1** watt. (WIFI)
 - RF 173 MHz: maximum output power of **1** watt. (Lojack)
- Total output power **10W**

All Frequency can mix very flexible; each module/Band is independent

Using Omni directional dipole antenna, gain value 2 ~ 3dBi.

- Each band can operate independently with DIP switch ON / OFF.
- Band power output per LED indicator ◦
- Battery: **Ni-MH battery 8000mHA** can support **2Hrs** of continuous working.
- Good heat dissipation, keep around 40°C when continuous operating.
- Built-in battery charger, you can charge while using support.
- Cover range: 10 ~ 30 M radius around the signal strength required for -80dBm based.
- Input voltage: AC 110-240V / 50-60Hz or DC 12.
- Support car charger.
- Weight: about 1.2 kg
- Size: 145 * 95 * 45 mm.
- Warranty time: One year.

